

BX-SO₂ sensor specification



Version: V1.0 Date: 2021.03.23

CATALOG

Instruction.....1

Functions.....1

Dimension.....2

Installation.....4

Connection.....5

Technical parameter.....6

Appendix.....7

 Sensor parameters quick guiding(1).....7

 Sensor parameters quick guiding(2).....8

CONTACT US.....9

Instruction

BX-SO₂ sulfur dioxide sensor adopts imported first-line big brand electrochemical sulfur dioxide sensor, which has the characteristics of quick and sensitive response and strong anti-interference ability. It is widely used in occasions where it is necessary to monitor the concentration of sulfur dioxide leakage. The product equipment adopts RS485 communication, and the communication stability is good. The shell has a high degree of protection and can adapt to various harsh conditions on site.


Functions

- The equipment adopts RS485 communication, standard ModBus-RTU communication protocol, and the communication stability is good;
- Adopt imported first-line big brand electrochemical sensor, stable and durable;
- High measurement accuracy, up to $\pm 3\%FS$;
- The product adopts a wall-mounted waterproof case, which is easy to install and has a high degree of protection, which can be used in harsh on-site environments.

Dimension



Unit : mm



Installation



Connection

When wiring, the number on the terminal of the machine should correspond to the number on the label on the product .

Cable Color	Instruction	mark
Brown	12V	Positive power
Black	GND	Negative power
Yellow	D+	Receive signal positive terminal
Blue	D-	Receive signal negative terminal

Technical parameter

Parameter	Specification
Power supply	DC12V
Max power	≤2W
Default range	0-20 ppm
Default precision	±3%FS
response	1s
Working temp	temp: -20 ~ 50°C
	humidity: 15 ~ 90%RH 0 ~ 80%RH
Communication	RS485 on board

Appendix

Sensor parameters quick guiding(1)

Product name	response(s)	Default range	Precision	Working temp	*Working humidity
Temp sensor	1	Temp sensor: -55°C~+125°C	Temp sensor: ±0.5°C	-10°C~+85°C	——
Temp &humidity sensor	1	Temp sensor: -40°C~+80°C	Temp sensor: ±0.5°C	-40°C~+80°C	——
		Humidity: 0~99.9%RH	Humidity: ±3%RH		
Brightness sensor	5	Brightness: 1~65535 lux	Brightness: ±20%	-40°C~+85°C	0%RH~80%RH
Wind speed sensor BX-FS(485)	1	wind speed: 0~60m/s	wind speed: ±0.3m/s	-40°C~+60°C	0%RH~80%RH
Wind direction sensor BX-FX(485)	1	wind direction: 0-359.9°	wind direction: ±1°	-40°C~+60°C	0%RH~80%RH
Noise sensor BX-ZS(485)	1	noise: 30dB~120dB	noise: ±0.5dB	-20°C~+60°C	0%RH~80%RH
Air quality sensor BX-PM(485)water proof	1	PM2.5: 0~6000ug/³	PM2.5、PM10: ±10%	-20°C~+60°C	0%RH~80%RH
		PM10: 0~6000ug/m³			
Environmental sensor BX-QX(485) waterproof	1	Temp sensor: -40°C~+120°C	Temp sensor: ±0.5°C	-20°C~+60°C	0%RH~80%RH
		Humidity: 0%RH~99%RH	Humidity: ±3%RH		
	1	noise: 30dB~120dB	noise: ±3db		
	1	PM2.5、PM10: 0-6000ug/m³	PM2.5、PM10: ±1ug/m³		

*The value ranges of the environmental Temp sensor and the environmental Humidity listed in the table refer to the working environment under which the sensor corresponds to the measurement accuracy;

*All sensors listed in the table are BX customized products, and are generally not directly compatible with similar sensors on the market.

Sensor parameters quick guiding(2)

Product name	Interface	transfer	Power supply
Temp sensor	one-wire	10-12 meters	3.0V~5.5V
Humidity sensor	one-wire	10-12 meters	3.0V~5.5V
Brightness sensor	I ² C	10-12 meters	3.0V~5.5V
wind speed sensor BX-FS(485)	RS485	no limit	12V or 24V power ≤0.5W
wind direction sensor BX-FX(485)	RS485	no limit	12V or 24V power ≤0.5W
Noise sensor BX-ZS(485)	RS485	no limit	12V or 24V power ≤0.5W
Air quality sensor BX-PM(485) waterproof	RS485	no limit	12V or 24V power ≤0.5W
BX-QX(485)waterproof-Humidity	RS485	no limit	12V or 24V power ≤1W
BX-QX(485)waterproof-noise	RS485	no limit	12V or 24V power ≤1W
BX-QX(485)waterproof- air quality	RS485	no limit	12V or 24V power ≤1W

CONTACT US

Shanghai ONBON Technology Co.,ltd (Headquarters)

Address: 7 Floor, Tower 88, 1199#, North Qinzhou Road, Xuhui District, Shanghai City,

China

Tel Phone: 086-21-64955136

Fax: 086-21-64955136

Website: www.onbonbx.com

ONBON (Jiangsu) Optoelectronic Industrial Co.,LTD

Address: 1299#, Fuchun Jiang Road, Kunshan City, Jiangsu Province, China

Sales Contacts

Tel: 0086-15921814956 0086-15800379719

Email: onbon@onbonbx.com

Second Development

Tel: 0512-66589212

Email: dev@onbonbx.com

iLEDCloud

Website: <http://www.iledcloud.com/>